


"And Gate" Socket Wiring (TOP)

(Circuit Board Side) (Rear Pins)

Pin Number

- | | | | | |
|-----|----------------|---|-----|----------------|
| 1. | + 12 vdc | ← + | 12. | "8" And Output |
| 2. | Ground | ← - | 13. | |
| 3. | |  | 14. | "8" And Input |
| 4. | "0" And Output | | 15. | |
| 5. | ' | | 16. | "7" And Output |
| 6. | "0" And Input | | 17. | |
| 7. | | | 18. | "7" And Input |
| 8. | "9" And Output | | 19. | |
| 9. | | | 20. | "6" And Output |
| 10. | "9" And Input | | 21. | |
| 11. | | | 22. | "6" And Input |

"And Gate" Socket Wiring (Bottom)

Pin Number

- | | | | |
|-----|----------------|-----|----------------|
| 1. | | 12. | "3" AND INPUT |
| 2. | "5" And Output | 13. | |
| 3. | | 14. | "2" And Output |
| 4. | "5" And Input | 15. | |
| 5. | | 16. | "2" And Input |
| 6. | "4" And Output | 17. | |
| 7. | | 18. | "1" And Output |
| 8. | "4" And Inp + | 19. | |
| 9. | | 20. | "1" And Input |
| 10. | "3" And Output | 21. | |
| 11. | | 22. | Gate Common |

Module Socket Wiring (TOP)
(Rear Pins)

Pin Number

1.	L7	12.
2.		13. "9" AND BUSS
3.	L8	14.
4.		15. "8" AND BUSS
5.	L9	16.
6.		17. "7" AND BUSS
7.	L0	18.
8.		19. "MG" BUSS
9.	"MR" BUSS	20.
10.		21. L6
11.	"0" AND BUSS	22. "6" AND BUSS

Module Socket Wiring (BOTTOM)
(Rear Pins)

Pin Number

1.	"5" AND BUSS	12.
2.		13. "1" AND BUSS
3.	L5	14.
4.		15. L1
5.	"4" AND BUSS	16.
6.		17. L2
7.	"3" AND BUSS	18.
8.		19. L3
9.	"2" AND BUSS	20.
10.		21. L4
11.	"S" Signal	22.

MODULE Socket Wiring (TOP)
(Front Pins)

Pin Number

- 2. "0" Ts signal
- 4. "9" " "
- 6. "8" " "
- 8. "7" " "
- 10. "6" " "

MODULE SOCKET WIRING (Bottom)
(Front Pins)

Pin Number

- 14. "5" Ts signal
- 16. "4" " "
- 18. "3" " "
- 20. "2" " "
- 22. "1" " "